

Design of Pulse Shapes and Digital Filters Based on Gaussian Functions

Edwin Hammerich

Ministry of Defence

Kulmbacher Str. 58-60, D-95030 Hof, Germany

Email: edwin.hammerich@ieee.org

August 31, 2008

Abstract

Two new pulse shapes for communications are presented. The first pulse shape is ISI-free and identical with the interpolating function (or ISI-free kernel) of a reconstruction formula in shift-invariant spaces with Gaussian generator. Several closed form representations in time and frequency domain are given including one for an approximation that is particularly simple. The second pulse shape is the root of the former and obtained by spectral factorization. As a consequence, shifted versions of it form an orthonormal system in the Hilbert space of finite-energy signals. The latter pulse shape is described as the response of an infinite-order digital FIR filter on a Gaussian function as input signal. Several equivalent versions of the digital filter including their finite-order approximations are presented. All filters enjoy the property that explicit formulas for their coefficients and poles are available. The filters are fully parametrizable with respect to bandwidth and sampling rate of the digital data.

1 Introduction

The main new result of the paper is the signal described in Theorem 3 of Section 3. This signal is the root of an interpolating function found earlier in context with sampling theorems based on Gaussian functions [5], [6]. "Extracting the root" was prompted by [15]. The proof of Theorem 3 is given in some detail. It is based on spectral factorization and uses notions and identities from the theory of q -analogs [14], [2]. Concepts of the latter theory normally arise in the context of combinatorics, number theory

and statistical mechanics, in the field of communications they seem to be new (apart from coding theory where they have a different meaning). In Sections 4 - 5 new digital filters are presented. Background material on sampling in shift-invariant spaces is discussed in Section 2 in some length.

The paper draws on previous work of Bhandari [3], [4], Unser [10], [11], [12], [13], Walter [8], and our own [5], [6], [7].

The following notation is used: $L^2(\mathbb{R})$ is the space of square integrable functions (or finite-energy signals) $f : \mathbb{R} \rightarrow \mathbb{C}$ with inner product $\langle f_1, f_2 \rangle = \int_{-\infty}^{\infty} f_1(x) \overline{f_2(x)} dx$. For the Fourier transform we adopt the convention $\hat{f}(\omega) = (2\pi)^{-1/2} \int_{-\infty}^{\infty} e^{-ix\omega} f(x) dx$, where x denotes time and ω (angular) frequency.

2 Sampling in Shift-Invariant Spaces Revisited

In the present section we give a review of sampling in shift-invariant spaces, its inherent difficulties and possible remedies.

Suppose that $\varphi \in L^2(\mathbb{R})$ is a continuous function, satisfies $\varphi(x) = O(|x|^{-1-\epsilon})$ as $x \rightarrow \pm\infty$ for some $\epsilon > 0$ and for any $\lambda \in \Lambda$, where Λ is some non-empty subset of $\mathbb{R}_+ = (0, +\infty)$, the family of functions $\{\varphi(\cdot - n\lambda); n \in \mathbb{Z}\}$ forms a Riesz basis in $L^2(\mathbb{R})$. Furthermore, we assume that for any $\lambda \in \Lambda$

$$\sum_{n=-\infty}^{\infty} \varphi(n\lambda) e^{-in\lambda\omega} \neq 0, \quad \omega \in \mathbb{R}. \quad (1)$$

An example is the Gaussian function

$$\varphi(x) = \frac{1}{\sqrt{2\pi}(1/\beta)} e^{-\frac{x^2}{2(1/\beta)^2}} \xleftrightarrow{\text{Fourier}} \hat{\varphi}(\omega) = \frac{1}{\sqrt{2\pi}} e^{-\frac{\omega^2}{2\beta^2}}, \quad (2)$$

where the bandwidth parameter β is an arbitrary positive real number.

The shift-invariant space $V_\lambda(\varphi)$ is defined as the closed linear span of $\{\varphi(\cdot - n\lambda); n \in \mathbb{Z}\}$ in $L^2(\mathbb{R})$. The following theorem asserts *perfect reconstruction* of any $f \in V_\lambda(\varphi)$ from sample values $f(n\lambda)$, $n \in \mathbb{Z}$, for any sampling interval $\lambda \in \Lambda$.

Theorem 1 *Let $\lambda \in \Lambda$. For any $f \in V_\lambda(\varphi)$ it holds that*

$$f(x) = \sum_{n \in \mathbb{Z}} f(n\lambda) \varphi_{\text{int}}(x - n\lambda), \quad x \in \mathbb{R}, \quad (3)$$

where the interpolating function $\varphi_{\text{int}} \in V_\lambda(\varphi)$ is given by¹

$$\begin{aligned}\hat{\varphi}_{\text{int}}(\omega) &= \frac{\hat{\varphi}(\omega)}{\sum_{n \in \mathbb{Z}} \varphi(n\lambda) e^{-in\lambda\omega}} \\ &= \frac{\hat{\varphi}(\omega)}{\frac{\Lambda}{\sqrt{2\pi}} \sum_{n \in \mathbb{Z}} \hat{\varphi}(\omega + n\Lambda)}, \quad \Lambda = \frac{2\pi}{\lambda}.\end{aligned}$$

This theorem is due to Walter [8], who proved it in case of an orthonormal system $\{\varphi(\cdot - n); n \in \mathbb{Z}\}$. The argument carries over to Riesz bases $\{\varphi(\cdot - n\lambda); n \in \mathbb{Z}\}$, see [6] for a Gaussian function φ . Then, φ_{int} is given by the right-hand side of Eq. (17) after substitution of τ by 2τ (see below) [6].

Unser [13] uses shift-invariant spaces of the form

$$V_T(\phi) = \left\{ f; f(x) = \sum_{n \in \mathbb{Z}} c_{T,n} \phi\left(\frac{x}{T} - n\right), c_T \in \ell^2 \right\}, \quad T > 0, \quad (4)$$

as means for *approximating* functions f lying in other subspaces of $L^2(\mathbb{R})$, for instance in the Sobolev space W_2^1 . Then, for the vanishing of the approximation error in the L^2 -norm as $T \rightarrow 0$ it is necessary and sufficient that the generating function ϕ satisfies additionally the partition of unity condition (PUC),

$$\forall x \in \mathbb{R} : \sum_{n \in \mathbb{Z}} \phi(x + n) = 1. \quad (5)$$

In our approach, the shift-invariant space has the form [6]

$$\begin{aligned}V_\lambda(\varphi) &= \left\{ f; f(x) = \sum_{n \in \mathbb{Z}} c_n \varphi(x - n\lambda), c \in \ell^2 \right\} \\ &= \left\{ f; f(x) = \sum_{n \in \mathbb{Z}} \frac{c_n}{\lambda} \varphi_\lambda\left(\frac{x}{\lambda} - n\right), c \in \ell^2 \right\},\end{aligned}$$

where $\varphi_\lambda(x) = \lambda\varphi(\lambda x)$, i.e., now $\phi = \varphi_\lambda$. Since by the Poisson summation formula it holds that

$$\sum_{n \in \mathbb{Z}} \varphi_\lambda(x + n) = \sqrt{2\pi} \sum_{n \in \mathbb{Z}} \hat{\varphi}\left(\frac{2\pi n}{\lambda}\right) e^{2\pi i n x}, \quad (6)$$

we retain an "approximate PUC" when $\lambda > 0$ becomes small enough under the assumption that $|\hat{\varphi}(\omega)|$ decays rapidly to 0 as $\omega \rightarrow \pm\infty$ and $\int_{\mathbb{R}} \varphi(x) dx =$

¹We make no difference between $\hat{\varphi}_{\text{int}}$ and $\widehat{\varphi_{\text{int}}}$ and so on.

1. Indeed, in case of a Gaussian function (2) we obtain with high accuracy

$$\sum_{n \in \mathbb{Z}} \varphi_\lambda(x+n) = 1 + \sum_{n \in \mathbb{Z} \setminus \{0\}} e^{-\frac{(2\pi n)^2}{2(\lambda\beta)^2}} e^{2\pi i n x} \approx 1, \quad x \in \mathbb{R}, \quad (7)$$

as $0 \leftarrow \lambda < 2/\beta$.

Anyway, a serious problem arises when resampling elements of a shift-invariant space. In practice, one often has samples $\{f(a+n\lambda)\}$ of $f \in V_\lambda(\varphi)$ with an offset $a \neq 0$. The following reconstruction formula can be derived (see [9] in case $\lambda = 1$):

$$f(x) = \sum_{n \in \mathbb{Z}} f(a+n\lambda) \varphi_{\text{int},a}(x-n\lambda), \quad x \in \mathbb{R}, \quad (8)$$

where the interpolating function $\varphi_{\text{int},a} \in V_\lambda(\varphi)$ is given by

$$\hat{\varphi}_{\text{int},a}(\omega) = \frac{\hat{\varphi}(\omega)}{\sum_{n \in \mathbb{Z}} \varphi(a+n\lambda) e^{-in\lambda\omega}}, \quad (9)$$

(provided that the denominator does not vanish). Since $\varphi_{\text{int},a}$ now depends on the often unknown offset a this raises a severe problem in practical applications.

One way out is to introduce a second function space, the so-called *localization space* to be defined next. For the rest of the paper we restrict ourselves on a Gaussian function φ as given in (2), for the general approach see [7]. Similarly to the classical sampling theorem we apply prior to sampling a prefilter

$$(\mathbf{P}_\varphi f)(x) = \int_{-\infty}^{\infty} f(y) \overline{\varphi(y-x)} dy = \int_{-\infty}^{\infty} e^{ix\omega} \overline{\hat{\varphi}(\omega)} \hat{f}(\omega) d\omega, \quad (10)$$

to an arbitrary finite-energy signal $f \in L^2(\mathbb{R})$ and the goal is to recover the filter output signal $g = \mathbf{P}_\varphi f$ from sample values $g(n\lambda)$, $n \in \mathbb{Z}$. The localization space of the prefilter,

$$\mathcal{P}_\varphi = \{g = \mathbf{P}_\varphi f; f \in L^2(\mathbb{R})\},$$

corresponds to the space of bandlimited signals in case of the classical sampling theorem. For the statement of the "approximate sampling theorem" (Theorem 2, see below) we also need the autocorrelation function of φ ,

$$\Phi = \mathbf{P}_\varphi \varphi \in \mathcal{P}_\varphi \xrightarrow{\text{Fourier}} \hat{\Phi}(\omega) = \sqrt{2\pi} |\hat{\varphi}(\omega)|^2, \quad (11)$$

again a Gaussian function. For arbitrary $\lambda \in \mathbf{\Lambda}$ we define the (second) interpolating function $\Phi_{\text{int}} \in \mathcal{P}_\varphi$ by its Fourier transform

$$\hat{\Phi}_{\text{int}}(\omega) = \frac{\hat{\Phi}(\omega)}{\frac{\Lambda}{\sqrt{2\pi}} \sum_{k \in \mathbb{Z}} \hat{\Phi}(\omega + k\Lambda)}, \quad \Lambda = 2\pi/\lambda. \quad (12)$$

Note that because of the Riesz basis condition on φ the denominator will never vanish [7]. In general $\Phi_{\text{int}} \neq \mathbf{P}_\varphi \varphi_{\text{int}}$.

Remark 1 *By representation (12) it is readily seen that*

$$\frac{\Lambda}{\sqrt{2\pi}} \sum_{n=-\infty}^{\infty} \hat{\Phi}_{\text{int}}(\omega + n\Lambda) = 1 \quad \forall \omega \in \mathbb{R}, \quad (13)$$

which is equivalent to $\Phi_{\text{int}}(n\lambda) = \delta_n \forall n \in \mathbb{Z}$, a necessary and sufficient condition for the set of shifted pulses $\{\Phi_{\text{int}}(x - n\lambda); n \in \mathbb{Z}\}$ to be ISI-free at points in time $x_n = n\lambda, n \in \mathbb{Z}$ [4].

In the Gaussian case we compute that

$$\hat{\Phi}_{\text{int}}(\omega) = \frac{\lambda}{\sqrt{2\pi}} \frac{e^{-\frac{i\pi}{\tau}(\omega/\Lambda)^2}}{\sqrt{-i\tau} \vartheta_3(\omega/\Lambda, \tau)}, \quad (14)$$

where

$$\vartheta_3(z, \tau) = \frac{1}{\sqrt{-i\tau}} \sum_{n=-\infty}^{\infty} e^{-\frac{i\pi}{\tau}(z+n)^2} \quad (15)$$

is one of the four theta functions [1] with parameter τ given by

$$\tau = \frac{i}{4\pi} (\lambda\beta)^2 \quad (i = \sqrt{-1}). \quad (16)$$

By inversion of the Fourier transform we obtain

$$\Phi_{\text{int}}(x) = \frac{i\pi\tau}{\vartheta_1'(0, -\frac{1}{\tau})} \frac{\vartheta_1(x/\lambda, -\frac{1}{\tau})}{\sinh(i\pi\tau x/\lambda)}, \quad (17)$$

where $\vartheta_1(z, \tau) = 2 \sum_{n=0}^{\infty} q^{(n+\frac{1}{2})^2} (-1)^n \sin[(2n+1)\pi z]$, $q = e^{i\pi\tau}$, $\Im(\tau) > 0$, is again a theta function [1]. When $\lambda \leq \beta^{-1}$ it holds with high accuracy that $\Phi_{\text{int}}(x) \approx S_0(x)$ where

$$S_0(x) = i\tau \frac{\sin(\pi x/\lambda)}{\sinh(i\pi\tau x/\lambda)}. \quad (18)$$

Note that in our setting $i\tau$ is always a negative real number. The following "approximate sampling theorem" is an instance of the Generalized Sampling Theorem [7, Theorem 3].

Theorem 2 *Let g be a signal in the localization space $\mathcal{P}_\varphi$ of $\mathbf{P}_\varphi$, i.e., $g = \mathbf{P}_\varphi f$ for some function $f \in L^2(\mathbb{R})$. Let $\lambda > 0$ and let the interpolating function Φ_{int} be given by (17). Then the function defined by*

$$\tilde{g}(x) = \sum_{n=-\infty}^{\infty} g(n\lambda) \Phi_{\text{int}}(x - n\lambda), \quad x \in \mathbb{R}, \quad (19)$$

is an element of the shift-invariant subspace $\mathcal{R}_\lambda(\varphi) \subseteq \mathcal{P}_\varphi$ which may be defined as the closed linear span of $\{\Phi(\cdot - n\lambda); n \in \mathbb{Z}\}$ in $L^2(\mathbb{R})$. Perfect reconstruction is obtained at the sampling instants,

$$\tilde{g}(n\lambda) = g(n\lambda), \quad n \in \mathbb{Z},$$

while for any other $x \in \mathbb{R}$ the reconstruction error is estimated by

$$|g(x) - \tilde{g}(x)|^2 \leq \frac{16\beta}{\sqrt{2\pi}} e^{-\frac{(\pi/\lambda)^2}{2\beta^2}} \int_{\mathbb{R}} |f(y)|^2 dy. \quad (20)$$

Consequently, the reconstruction error decays superexponentially to 0 as $0 \leftarrow \lambda < 1/\beta$.

In the specific case of a Gaussian function as considered here it is shown in [6] that the reconstruction error becomes small already when $\lambda = 1/\beta$ (provided that the energy $\int_{\mathbb{R}} |f(x)|^2 dx$ of the input signal f is not too large).

Since the localization space $\mathcal{P}_\varphi$ is invariant with respect to arbitrary translations $g \rightarrow g_a = g(a + \cdot)$, $a \in \mathbb{R}$, the reconstruction formula (19) applied to sample values $\{g(a + n\lambda); n \in \mathbb{Z}\}$ now simply results in an approximation $\tilde{g}_a \in \mathcal{R}_\lambda(\varphi)$ to $g_a \in \mathcal{P}_\varphi$. So, we get rid of the problems concerning an unknown offset mentioned earlier.

Remark 2 *The Fourier transform of function S_0 as in (18) is given by*

$$\hat{S}_0(\omega) = -\frac{\lambda}{\sqrt{2\pi}} \frac{\sinh\left(\frac{\pi}{i\tau}\right)}{\cosh\left(\frac{\pi}{i\tau}\right) + \cosh\left(\frac{\lambda\omega}{i\tau}\right)}, \quad \lambda > 0,$$

and forms a simple though very good approximation to $\hat{\Phi}_{\text{int}}(\omega)$, $\omega \in \mathbb{R}$, when $\lambda \leq 1/\beta$.

3 Spectral Factorization of the Interpolating Function

We start by compiling some prerequisites.

Definition 1 For any $a \in \mathbb{R}$ and $q \in \mathbb{C}$, $|q| < 1$, the q -Pochhammer symbol $(a; q)_n$ is defined by

$$\begin{aligned} (a; q)_n &= (1 - a)(1 - aq) \cdots (1 - aq^{n-1}), n = 1, 2, \dots \\ (a; q)_\infty &= \lim_{n \rightarrow \infty} (a; q)_n \\ (a; q)_0 &= 1. \end{aligned}$$

The following identities of Euler (see, e.g., [2]) hold for any $q \in \mathbb{C}$, $|q| < 1$:

$$1 + \sum_{n=1}^{\infty} \frac{q^{\frac{1}{2}n(n-1)}}{(q; q)_n} z^n = \prod_{n=0}^{\infty} (1 + zq^n), \quad z \in \mathbb{C}, \quad (21)$$

$$1 + \sum_{n=1}^{\infty} \frac{z^n}{(q; q)_n} = \prod_{n=0}^{\infty} (1 - zq^n)^{-1}, \quad |z| < 1. \quad (22)$$

Only Eq. (21) will be used in the proof of the next theorem. The Jacobi triple product identity [2]

$$\sum_{n=-\infty}^{\infty} q^{n^2} z^n = \prod_{n=1}^{\infty} (1 - q^{2n})(1 + q^{2n-1} z^{-1})(1 + q^{2n-1} z) \quad (23)$$

will also be needed. In our case always

$$q = e^{i\pi\tau}, \quad (24)$$

where the parameter τ is as in (16). The special q -Pochhammer symbols²

$$(q^2; q^2)_n = \prod_{k=1}^n (1 - q^{2k}), \quad Q_0 := (q^2; q^2)_\infty$$

will occur frequently.

Theorem 3 For the signal

$$\varphi_{\text{ortho}}(x) = \frac{1}{\sqrt{(q^2; q^2)_\infty}} \sum_{n=0}^{\infty} \frac{(-q)^n}{(q^2; q^2)_n} \phi(x - n\lambda), \quad (25)$$

where

$$\phi(x) = \frac{\beta^{1/2}}{\pi^{1/4}} e^{-\frac{\beta^2}{2} x^2} \quad (26)$$

is the Gaussian function (2) normalized to unit energy, $\int_{\mathbb{R}} |\phi(x)|^2 dx = 1$, it holds that

$$\hat{\Phi}_{\text{int}}(\omega) = \sqrt{2\pi} |\hat{\varphi}_{\text{ortho}}(\omega)|^2, \quad \omega \in \mathbb{R}. \quad (27)$$

²In the theory of q -analogs [14] the "q" is a generic name standing for q , q^2 , $-q$ etc.

Proof. The definition (14) of the interpolating function Φ_{int} in Fourier domain may be written as

$$\hat{\Phi}_{\text{int}}(\omega) = \sqrt{2\pi}\lambda \frac{|\hat{\varphi}(\omega)|^2}{\sqrt{-i\tau}\vartheta_3(\omega/\Lambda, \tau)}.$$

Then, Eq. (27) becomes

$$|\hat{\varphi}_{\text{ortho}}(\omega)|^2 = \lambda \frac{|\hat{\varphi}(\omega)|^2}{\sqrt{-i\tau}\vartheta_3(\omega/\Lambda, \tau)}.$$

Since the theta function $\vartheta_3(z, \tau)$ in (15) has the second representation [1]

$$\begin{aligned} \vartheta_3(z, \tau) &= 1 + 2 \sum_{n=0}^{\infty} q^{n^2} \cos(2\pi n z) \\ &= \sum_{n=-\infty}^{\infty} q^{n^2} e^{2\pi i n z}, \quad z \in \mathbb{C}, \end{aligned}$$

we obtain by setting

$$P(z) = \prod_{n=1}^{\infty} (1 + q^{2n-1} z^{-1})$$

in virtue of identity (23) the factorization

$$\vartheta_3(\omega, \tau) = Q_0^{1/2} P(e^{2\pi i \omega}) \cdot \overline{Q_0^{1/2} P(e^{2\pi i \omega})}, \quad \omega \in \mathbb{R}.$$

Since the real-valued function $\vartheta_3(\cdot, \tau)$ is positively lower bounded on $\mathbb{R}$ so is the function $\omega \rightarrow |P(e^{2\pi i \omega})|$. As a consequence, the definition in Fourier domain

$$\hat{\varphi}_{\text{ortho}}(\omega) = \lambda^{\frac{1}{2}} \frac{\hat{\varphi}(\omega)}{(-i\tau)^{1/4} Q_0^{1/2} P(e^{2\pi i \omega/\Lambda})},$$

will result in a function $\varphi_{\text{ortho}} \in L^2(\mathbb{R})$ satisfying condition (27).

Next, we need to invert the Fourier transform. Since $\omega \rightarrow 1/P(e^{2\pi i \omega})$ is a bounded 1-periodic function it is in $L^2([0, 1))$ and has a Fourier series expansion $1/P(e^{2\pi i \omega}) = \sum_{n=-\infty}^{\infty} a_n e^{-2\pi i n \omega}$, $(a_n)_{n \in \mathbb{Z}} \in \ell^2(\mathbb{Z})$, where

$$a_n = \int_0^1 e^{2\pi i n \omega} \frac{1}{P(e^{2\pi i \omega})} d\omega, \quad n \in \mathbb{Z}. \quad (28)$$

By inverse Fourier transform we now obtain

$$\begin{aligned}
\varphi_{\text{ortho}}(x) &= c \frac{1}{\sqrt{2\pi}} \int_{-\infty}^{\infty} e^{ix\omega} \frac{1}{P(e^{2\pi i\omega/\Lambda})} \hat{\varphi}(\omega) d\omega, \quad c = \frac{\lambda^{\frac{1}{2}}}{(-i\tau)^{1/4} Q_0^{1/2}} \\
&= c \sum_{n=-\infty}^{\infty} \frac{a_n}{\sqrt{2\pi}} \int_{-\infty}^{\infty} e^{i(x-n\lambda)\omega} \hat{\varphi}(\omega) d\omega \\
&= c \sum_{n=-\infty}^{\infty} a_n \varphi(x - n\lambda) \\
&= \frac{1}{Q_0^{1/2}} \sum_{n=-\infty}^{\infty} a_n \phi(x - n\lambda).
\end{aligned}$$

The computation of the coefficients (28) is accomplished in the complex domain.

Case $n = -1, -2, \dots$: After substitution of ω by $1 - \omega$ we obtain

$$\begin{aligned}
a_n &= \int_0^1 e^{-2\pi i n \omega} \frac{1}{P(e^{-2\pi i \omega})} d\omega \\
&= \frac{1}{2\pi i} \oint_{|z|=1} \frac{z^{-n-1}}{P(z^{-1})} dz,
\end{aligned}$$

where integration in the latter integral is performed counterclockwise around the unit circle. Since the integrand function is analytic within a neighbourhood of the closed unit disc, we obtain $a_n = 0$, $n = -1, -2, \dots$.

Case $n = 0, 1, \dots$: We now have

$$\begin{aligned}
a_n &= \frac{1}{2\pi i} \oint_{|z|=1} \frac{z^{n-1}}{P(z)} dz \\
&= \lim_{M \rightarrow \infty} \underbrace{\frac{1}{2\pi i} \oint_{|z|=1} \frac{z^{n-1}}{P_M(z)} dz}_{I_M(n)},
\end{aligned}$$

where

$$P_M(z) = \prod_{k=0}^{M-1} (1 + q^{2k+1} z^{-1}), \quad M = 1, 2, \dots,$$

and the path of integration is same as before. The integrand function in the integral defining $I_M(n)$ has simple poles in

$$z_m = -q^{2m+1}, \quad m = 0, 1, \dots, M-1,$$

within the unit circle. By means of the theorem of residues we obtain

$$I_M(n) = \sum_{m=0}^{M-1} \operatorname{Res}_{z_m} \frac{z^{n-1}}{P_M(z)},$$

whence

$$a_n = \lim_{M \rightarrow \infty} I_M(n) = \sum_{m=0}^{\infty} \operatorname{Res}_{z_m} \frac{z^{n-1}}{P(z)}.$$

We compute that

$$\begin{aligned} \operatorname{Res}_{z_m} \frac{z^{n-1}}{P(z)} &= \operatorname{Res}_{z_m} \frac{z^n}{zP(z)} \\ &= \frac{z_m^n}{\prod_{\substack{k=0 \\ k \neq m}}^{\infty} (1 + q^{2k+1} z_m^{-1})} \\ &= \frac{(-q)^n q^{2mn}}{(q^2; q^2)_{\infty} \prod_{k=1}^m (1 - q^{-2k})} \\ &= \frac{(-q)^n}{(q^2; q^2)_{\infty}} \frac{(-1)^m q^{m(m+1)} (q^{2n})^m}{\prod_{k=1}^m (1 - q^{2k})}. \end{aligned}$$

After substitution of q by q^2 Eq. (21) becomes

$$1 + \sum_{n=1}^{\infty} \frac{q^{n(n-1)}}{(q^2; q^2)_n} z^n = \prod_{n=0}^{\infty} (1 + zq^{2n}).$$

Hence

$$\begin{aligned} a_n &= \frac{(-q)^n}{(q^2; q^2)_{\infty}} \sum_{m=0}^{\infty} \frac{q^{m(m-1)}}{(q^2; q^2)_m} (-q^{2(n+1)})^m \\ &= \frac{(-q)^n}{(q^2; q^2)_{\infty}} \prod_{k=0}^{\infty} (1 - q^{2(n+1)} q^{2k}) \\ &= \frac{(-q)^n}{(q^2; q^2)_n}, \end{aligned}$$

which concludes the proof of Theorem 3.

Remark 3 (cf. [3], [4]) *a) It is well-known that for an arbitrary function $s \in L^2(\mathbb{R})$ the system of functions $\{s(x - n\lambda); n \in \mathbb{Z}\}$ forms an orthonormal system in $L^2(\mathbb{R})$ if and only if*

$$\Lambda \sum_{n=-\infty}^{\infty} |\hat{s}(\omega + n\Lambda)|^2 = 1 \quad \text{a.e.,}$$

where Λ is as in (12). For the signal $s(x) = \varphi_{\text{ortho}}(x)$ in Theorem 3 this is fulfilled because of Eqs. (13) and (27) (hence the subscript notation).

b) At the receiver's side the filter $\mathbf{P}_{\varphi_{\text{ortho}}}$ obtained after substitution in (10) the Gaussian function φ by φ_{ortho} forms a matched filter allowing optimal receipt of the signals $s(x - n\lambda) = \varphi_{\text{ortho}}(x - n\lambda)$ in the presence of noise. Moreover, because $\{\varphi_{\text{ortho}}(\cdot - n\lambda); n \in \mathbb{Z}\}$ forms an orthonormal system ISI is cancelled in the output of the receiver filter $\mathbf{P}_{\varphi_{\text{ortho}}}$ at the points in time $x_n = n\lambda$, $n \in \mathbb{Z}$.

In view of Theorem 2 we regard $\lambda = 1/\beta$ as the "natural" step size with respect to bandwidth parameter β .

4 Digital Filters

Substitution of q by q^2 in Eqs. (21) and (22) and, subsequently, of z by qz^{-1} and $-qz^{-1}$, resp., results in the identities

$$1 + \sum_{n=1}^{\infty} \frac{q^{n^2}}{(q^2; q^2)_n} z^{-n} = \prod_{n=0}^{\infty} (1 + q^{2n+1} z^{-1}), \quad (29)$$

$$1 + \sum_{n=1}^{\infty} \frac{(-q)^n}{(q^2; q^2)_n} z^{-n} = \prod_{n=0}^{\infty} \frac{1}{1 + q^{2n+1} z^{-1}}. \quad (30)$$

For $N = 1, 2, \dots$ we define the functions

$$\begin{aligned} H_1^N(z) &= 1 \left/ \left(1 + \sum_{n=1}^N \frac{q^{n^2}}{(q^2; q^2)_n} z^{-n} \right) \right., \\ H_2^N(z) &= \prod_{n=0}^{N-1} \frac{1}{1 + q^{2n+1} z^{-1}}, \\ H_3^N(z) &= 1 + \sum_{n=1}^N \frac{(-q)^n}{(q^2; q^2)_n} z^{-n}. \end{aligned}$$

Since by Eqs. (29), (30) it holds that

$$\lim_{N \rightarrow \infty} H_1^N(z) = \lim_{N \rightarrow \infty} H_2^N(z) = \lim_{N \rightarrow \infty} H_3^N(z), \quad |z| \geq 1,$$

for sufficiently large N the functions $H_k^N(z)$, $k = 1, 2, 3$, are approximations of each other.

$H_1^N(z)$ is the transfer function of an IIR filter of order N , $H_3^N(z)$ of a FIR filter of the same order, and $H_2^N(z)$ represents a cascade of N IIR filters of order 1. All three filters are causal filters. Recall that parameter q defined by (16), (24) depends on parameters β controlling bandwidth of the filter and λ defining sampling interval of the discrete data. β, λ may be chosen independently and arbitrarily within $(0, +\infty)$. $H_3^N(z)$ is a finite order approximation to the digital time-domain filter used in (25).

Because B-splines [12] with increasing order converge to Gaussian functions it is worthwhile to compare digital filters based on Gaussian functions with their B-spline based counterparts [10], [11]. The digital filter with transfer function

$$\begin{aligned} H_4^N(z) &= \prod_{n=0}^{N-1} \frac{1}{(1 + q^{2n+1}z^{-1})(1 + q^{2n+1}z)} \\ &= H_2^N(z^{-1})H_2^N(z), \end{aligned}$$

a combination of a causal and an anticausal recursive filter, corresponds to the so-called direct B-spline filter [10, (3.15)] occurring also in [3, Section IV]. Note that in contrast to the numerical values in [11, Table I] the poles of $H_4^N(z)$ within the unit circle are described by a simple formula,

$$z_n = -q^{2n+1}, \quad n = 0, 1, \dots, N-1, \quad (31)$$

where $q \in (0, 1)$ is explicitly given by (16), (24). There are no poles on the unit circle.

5 Implementation

The digital filters with transfer functions $H_k^N(z)$, $k = 1, 2, 3$, of the previous section should now be implemented and evaluated. Note that the parameter $q < 1$ as in (24) becomes close to 1 as the time-frequency product $\lambda\beta$ in (16) becomes small. This would result in digital filters of high order N . Then, the recursive IIR filter $H_1^N(z)$ might be the best choice, because the factor n^2 in the exponent of the coefficients ensures faster decay resulting in a much lower order N needed.

However, for the computation of the sample values $\varphi_{\text{ortho}}(m\lambda)$, $m \in \mathbb{Z}$, of the presumably useful pulse form (25) by

$$\varphi_{\text{ortho}}(m\lambda) = Q_0^{-1/2} \sum_{n=0}^{\infty} \frac{(-q)^n}{(q^2; q^2)_n} \phi((m-n)\lambda)$$

only a few filter coefficients are involved because of the fast decay of the Gaussian function ϕ as in (26).

A second useful pulse form is the interpolating function Φ_{int} of (14) because of its ISI-freeness. Here the question arises how to realize it technically. The solution given in form of the ISI-free kernel in [3, (7)] would consist in sending the Gaussian function Φ as in (11) through a digital filter with coefficients $(\Phi(k))^{-1}$ (case $\lambda = 1$). A finite order approximation is the digital filter $H_4^N(z)$ of the previous section (up to a constant factor we didn't care so far). The implementation of the related direct B-spline filter described in [11, (2.5)] should carry over to our case with minor changes (if any). An implementation of the latter filter would be interesting on its own, see [3, Section IV] and [10, Section III-C].

References

- [1] M. Abramowitz and I.A. Stegun, *Handbook of Mathematical Functions*, Dover Publ., New York, NY 1972.
- [2] G.E. Andrews, *The Theory of Partitions*, Cambridge University Press, Cambridge, UK, 1998.
- [3] A. Bhandari, Sampling Theorems and the Nyquist Criteria: A Unifying Approach, IEEE, 2007.
- [4] A. Bhandari, Splines and ISI Free Communication: Schoenberg meets Nyquist, IEEE ISSPA, Sharjah, 2007.
- [5] E. Hammerich, A sampling theorem for time-frequency localized signals, *Sampl. Theory Signal Image Process.*, **3**, 45-81, 2004.
- [6] E. Hammerich, Sampling in shift-invariant spaces with Gaussian generator, *Sampl. Theory Signal Image Process.*, **6**, 71-86, 2007.
- [7] E. Hammerich, A generalized sampling theorem for frequency localized signals, to be published.
- [8] G.G. Walter, A sampling theorem for wavelet subspaces, *IEEE Trans. Inform. Theory*, **38**, 881-884, 1992.
- [9] G. G. Walter and X. Shen, *Wavelets and other orthogonal systems*, Chapman & Hall/CRC, Boca Raton, 2001.

- [10] M. Unser, A. Aldroubi, and M. Eden, B-Spline Signal Processing: Part I–Theory, *IEEE Trans. Sig. Proc.*, **41**, 821-832, 1993.
- [11] M. Unser, A. Aldroubi, and M. Eden, B-Spline Signal Processing: Part II–Efficient Design and Applications, *IEEE Trans. Sig. Proc.*, **42**, 834-848, 1993.
- [12] M. Unser, Splines: A perfect fit for signal and image processing, *IEEE Sig. Proc. Mag.*, **16**, 22-38, 1999
- [13] M. Unser, Sampling - 50 years after Shannon, *Proc. IEEE*, **88**, 569-587, 2000.
- [14] E.W. Weisstein, q-Analog, [Online]. Available: <http://mathworld.wolfram.com/q-Analog.html>
- [15] U. Zölzer, personal communication, Helmut-Schmidt-Universität Hamburg, 16.04.2007.